# 4”, 6”, 8”, 10” CCT & WATTAGE SELECTABLE COMMERCIAL DOWNLIGHT
# LT23975, LT23976, LT23977, LT23978

**SAFETY PRECAUTIONS:** FOR SAFETY, READ AND UNDERSTAND INSTRUCTIONS COMPLETELY BEFORE STARTING INSTALLATION. ELECTRICITY SHOULD BE TURNED OFF AT THE FUSE OR THE CIRCUIT BREAKER BOX BEFORE INSTALLING THE FIXTURE. ALL ELECTRICAL CONNECTIONS MUST BE IN ACCORDANCE WITH N.E.C. OR YOUR LOCAL CODE.

DANGER - RISK OF SHOCK - DISCONNECT POWER BEFORE INSTALLATION

DANGER - RISQUE DE CHOC - COUPER L’ALIMENTATION AVANT L’INSTALLATION

**CAUTION:**
**DISCONNECT POWER BEFORE CONNECTING THE FIXTURE. FAILURE TO DO SO MAY PERMANENTLY DAMAGE THE LEDs.**

**WARNING:** For wet location installation, after fixture is installed on ceiling, put silicone glue to seal the gap between fixture and ceiling.

## NEW CONSTRUCTION INSTALLATION

1. Make sure the POWER IS TURNED OFF at the source to the recessed housing in which you are installing the product.
2. Fix the ceiling or other fixed parts of the junction box and hook the safety cord to the junction box or other place (FIG. 1)
3. Insert lamp conduit into the J-Box and wire to power source (black to hot, white to neutral, green to ground) (FIG. 2)
4. Adjust the lamp power to desired lumen output by sliding the selector switch (FIG. 3)
5. Squeeze the two housing clips so they are in an upright position and insert lamp into housing (FIG. 4)
6. Once lamp is inside the housing, release the housing clips and continue pushing lamp into housing until securely fixed in the ceiling. (FIG. 5)

USE THE TEMPLATE



**NOTE: The junction box is fixed on the ceiling bracket.**

FIG. 1



ATTACH SAFETY CLIP

FIG. 2



WIRE TO J-BOX

CONNECTING THE WIRES




| | | |
|---|---|---|
| FIXTURE WIRES Black or Smooth | | HOUSE WIRES Black (Hot) |
| FIXTURE WIRES White or Ribbed | | HOUSE WIRES White (Neutral) |
| FIXTURE WIRES Bare Copper (Ground) | | HOUSE WIRES Green or Bare Copper (Ground) |

FIG. 3



ADJUST WATTAGE AND CCT TO DESIRED OUTPUT

FIG. 4



PUSH CLIPS UP & INSTALL INTO OPENING

FIG. 5



ENSURE FIXTURE IS FLUSH. INSTALLATION IS COMPLETE

## CUTOUT SIZE

**LT23975**
CUTOUT: Ø 4.3”
(110 MM)

**LT23976**
CUTOUT: Ø 6.3”
(160 MM)

**LT23977**
CUTOUT: Ø 7.87”
(200 MM)

**LT23978**
CUTOUT: Ø 9.64”
(245 MM)

TEL: 856-234-2211 FAX: 856-234-0881 www.lum-tech.com

LUM-TECH LIGHTING